

Indianapolis\_3035 N. Shadeland Ave., Indianapolis, IN 46226\_800.MMC.HVAC •• Sparks\_905 Southern Way, Sparks, NV 89431\_800.884.4MMC •• Longview\_201 Kodak Blvd., Longview, TX 75602\_903.248.4800

	MicroMetl	Date: 2/17/2025	Weights:	191lbs/86.64kg	Units:		Part Number: PECD-SRT12CB-D2DH-4L1
Submit	ted To: guest@microm	etl.com		Job:		Notes:	
Adjustat Included JC2	ble Dry Bulb Sensor, 460 <sup>v</sup> I. Electrical junction box p mpliant Economizer:	Volt Three Phas rovided. High vo	e, Modulating, I bitage cable to b	Designed To Operat	al with Honeywell Jade W7220 Single/Multiple te At 2675 CFM @ 1/2" - 1 HP. Power Exhaust I installed. Power Exhaust VFD is BacNet Com 2016 prescriptive section 140.4 (damper leakag	Painted To Match RTU, Al patible. For Differential ser	I Necessary Panels And Hardware nsor please order 9901-2022-DIFF
•	and Diagnostic controls	,		/ 0010 dama and a d			tion and Discussion
2.	requirements in section		IKAE 90.1-2013	0/2016 damper leal	kage requirements as stated in Table 6.4.3.4.3.	, and meet 2016 Fault Dete	ection and Diagnosis
3.	IECC: Economizers me requirements, and IECC				sections C403.2.4.3 and C403.3.3.5 for outside Diagnostic requirements.	air, return air, and relief da	amper (when provided) leakage
4.	<b>AMCA:</b> Outside air and provided) are also AMC.				ated at 1" w.g. Refer to MicroMetl NS2 catalog s site for details.	heet on web site for details	s. Relief air dampers (when

## Features:

- Includes ECD-SRT12CA Series Economizer. See economizer submittal for economizer details.
- Designed specifically for vertical discharge applications. Easy to install. Easy to service.
- Includes assembled rainhood with aluminum water entrainment filters in the outside air section.
- Rainhood is sloped for water run-off.
- Built-in barometric relief damper provided.
- All harnesses and plugs needed are provided.
- Uses standard factory filter access door shipped with HVAC unit.
- If factory hinged access door option is installed on unit, an additional kit is required to seal hinged door properly.
   OEM part no. CRPECONV003A00 or MicroMetl part number 0640-0100-HDANGL

## Notes:

- 1. Control systems include Honeywell W7220 JADE controller, mixed (supply) air temperature sensor, OA sensor in description, and spring-return communicating actuator (some include differential return sensor as noted).
- 2. JADE W7220 controller is field mounted in unit's control box.
- 3. Mixed (supply) air sensor is field installed in indoor blower fan section.
- 4. Differential return sensor (MicroMetl Part No. 9901-2022-DIFF JC2) is field installed in return duct.
- ASHRAE, IECC, and Title 24 require the economizer controller be capable of reporting faults to a fault management application accessible by day-to-day operating or service personnel, or annunciated locally on zone thermostats or in some codes other devices are acceptable. Refer to applicable code requirements and to MicroMetl instructions for suggestions.
- 6. For older single speed models without the Central Terminal Board the "-D2" part number is replaced by "-DJ". (See separate submittal).

The Information contained in this drawing is the sole property of Micrometl Corporation. Any reproduction in part or whole without the written permission of Micrometl Corporation is prohibited.

Indianapolis\_3035 N. Shadeland Ave., Indianapolis, IN 46226\_800.MMC.HVAC •• Sparks\_905 Southern Way, Sparks, NV 89431\_800.884.4MMC •• Longview\_201 Kodak Blvd., Longview, TX 75602\_903.248.4800



MicroMetl Corporation certifies that the models GR1 and NS2 shown herein are licensed to bear the AMCA Seal. The ratings shown are based on tests and procedures performed in accordance with AMCA Publication 511 and comply with requirements of the AMCA Certified Ratings Programs. The AMCA Certified Ratings Seal applies to Air Leakage and Air Performance ratings.

MicroMetl	Date: 2/17/2025	Weights:	191lbs/86.64kg	Units:		Part Number: PECD-SRT12CB-D2DH-4L1
Submitted To: guest@micron	netl.com		Job:		Notes:	
	1.1 C D 1	0				

Economizer & Power Exhaust Combination Package, Genesis Ultra Low Leak Vertical with Honeywell Jade W7220 Single/Multiple Speed Electromechanical Controller, Honeywell Actuator, Adjustable Dry Bulb Sensor, 460 Volt Three Phase, Modulating, Designed To Operate At 2675 CFM @ 1/2" - 1 HP. Power Exhaust Painted To Match RTU, All Necessary Panels And Hardware Included. Electrical junction box provided. High voltage cable to be field supplied and installed. Power Exhaust VFD is BacNet Compatible. For Differential sensor please order 9901-2022-DIFF JC2..

<ul> <li>- 1/2HP Power Exhaust Configurations and Electrical Data</li> </ul>									
Suffix	Voltage	Phase	Description	HP	FLA	MCA	MOCP	Internally Provided Fuses	
1VH	208-230/240	1	Constant Volume	0.5	4.1-4.3	5.1-5.4	9.2-9.7	N/A	
2VH	208-230/240	3	Constant Volume	0.5	2.3-2.2	2.9-2.8	5.2-5.0	N/A	
1LH or 1TH	208-230/240	1	Modulating	0.5	5.7*	7.1	12.8	10 Amp	
2LH or 2TH	208-230/240	3	Modulating	0.5	3.9*	4.9	8.8	10 Amp	
4VH	460/480	3	Constant Volume	0.5	1.1	1.4	2.5	N/A	
4LH or 4TH	460/480	3	Modulating	0.5	1.5*	1.9	3.4	10 Amp	

<ul> <li>- 1HP Power Exhaust Configurations and Electrical Data</li> </ul>										
Suffix	Voltage	Phase	Description	HP	FLA	MCA	MOCP	Internally Provided Fuses		
2V1	208-230/240	3	Constant Volume	1.0	3.8-3.6	4.8-4.5	8.6-8.1	N/A		
1L1	208-230/240	1	Modulating	1.0	10.0*	12.5	22.5	20 Amp		
L1 or 2T1	208-230/240	3	Modulating	1.0	6.4*	8.0	14.4	12 Amp		
4V1	460/480	3	Constant Volume	1.0	1.9	2.4	4.3	N/A		
L1 or 4T1	460/480	3	Modulating	1.0	2.8*	3.5	6.3	10 Amp		
4V1	460/480	3	Constant Volume	1.0	1.9	2.4	4.3			

\*VFD Input Current

The Information contained in this drawing is the sole property of Micrometl Corporation. Any reproduction in part or whole without the written permission of Micrometl Corporation is prohibited.

Indianapolis\_3035 N. Shadeland Ave., Indianapolis, IN 46226\_800.MMC.HVAC •• Sparks\_905 Southern Way, Sparks, NV 89431\_800.884.4MMC •• Longview\_201 Kodak Blvd., Longview, TX 75602\_903.248.4800

	Nro M	Af Date:	We	eights:	101160/00 011/2	Units:					F	Part Number:
	croM	eu <sub>2/17/</sub>	2025		191lbs/86.64kg							PECD-SRT12CB-D2DH-4L
bmitted To	: guest@n	nicrometl.con	n		Job:				Not	es:		
onomizer & F	Power Exha	ust Combinatio	on Package,	Genesis Ul	tra Low Leak Vert	ical with Hor	neywell Jade \	N7220 Single	/Multiple Spee	d Electrom	echanical Co	ontroller, Honeywell Actuator,
			-				•	-				lecessary Panels And Hardware
•				-			-					or please order 9901-2022-DIFF
2	··· ,· ···		5		· · · · · · · · · · · ·							- F
			- Seri	es Low	Static Power	Exhaust	Configura	tions and	Electrical D	Data		
	F	Suffix	Voltage	Phase	Descriptio	10.0000.00	FLA	MCA	MOCP	Inte	ernally led Fuses	
	F	1VH	208-230	1	Constant Volu	ume 0.5	4.1-4.3	5.1-5.4	9.2-9.7		N/A	-
	F	2VH	208-230	3	Constant Volu		2.3-2.2	2.9-2.8	5.2-5.0	-	N/A	
		1LH or 1TH		1	Modulating		5.7*	7.1	12.8	10	Amp	1
	1	2LH or 2TH	230	3	Modulating	g 0.5	3.9*	4.9	8.8	10	Amp	1
		4VH	460	3	Constant Volu	ume 0.5	1.1	1.4	2.5		N/A	
	•	4LH or 4LH	460	3	Modulating	g 0.5	1.5*	1.9	3.4	10	) Amp	]
			- Serie	es <u>High</u>	Static Power	Exhaust	Configura	tions and	Electrical D			
		Suffix	Voltage	Phase	Description	ו HP	FLA	MCA	MOCP	Inte Provide	rnally ed Fuses	
		2V1	208-230		Constant Volu		3.8-3.6	4.8-4.5	8.6-8.1		N/A	
	H	1L1	208-230	1	Modulating		10.0*	12.5	22.5		Amp	
		2L1 or 2T1	230	3	Modulating	1.0	6.4*	8.0	14.4	12	Amp	
						· · · · · · · · · · · · · · · · · · ·						
		4V1	460	3	Constant Volu	me 1.0	1.9	2.4	4.3	1	N/A	
	_	4L1 or 4T1	460 460		Constant Volu Modulating	· · · · · · · · · · · · · · · · · · ·		2.4 3.5	4.3 6.3	1		
	_	4L1 or 4T1 *VFD Input	460 460 Current	3	Modulating	me 1.0 1.0	1.9 2.8*	3.5	6.3	10 N	I/A Amp	
CFM	_	4L1 or 4T1 *VFD Input	460 460 Current 1/2 HP" Freg.	3		me 1.0 1.0	1.9 2.8*	3.5	6.3	10 N	I/A Amp	Blower Outlet dBA @ 5f
	ESP	4L1 or 4T1 *VFD Input RPM	460 460 Current <b>1/2 HP''</b>	3 3 Sound 63	Modulating Data - Ass 125	me 1.0 1.0	1.9 2.8* 3125 Inte 500	3.5 ernal Ex 1000	6.3 haust Ca 2000	binet S	V/A Amp Static. 8000	Blower Outlet dBA @ 5f
2200	<b>ESP</b>	4L1 or 4T1 *VFD Input RPM 712	460 460 Current 1/2 HP" Freg.	3 3 <b>Sound</b> 63 76	Modulating Data - Ass 125 74	me 1.0 1.0 250 71	1.9 2.8* 3125 Inte 500 69	3.5 ernal Ex 1000 68	6.3 haust Ca	10 binet S	Amp	62
	ESP	4L1 or 4T1 *VFD Input RPM	460 460 Current 1/2 HP" Freg.	3 3 Sound 63	Modulating Data - Ass 125	me 1.0 1.0	1.9 2.8* 3125 Inte 500	3.5 ernal Ex 1000	6.3 haust Ca 2000 65	<b>binet S</b> 4000 61	V/A Amp Static. 8000 58	
2200 2075	<b>ESP</b> 0.1 .25	4L1 or 4T1 *VFD Input RPM 712 760	460 460 Current 1/2 HP" Freg.	3 3 <b>Sound</b> 63 76 78	Modulating Data - Ass 125 74 76	me 1.0 1.0 250 71 74	1.9 2.8* 3125 Inte 500 69 71	3.5 ernal Ex 1000 68 70	6.3 haust Ca 2000 65 68	binet S 4000 61 64	V/A Amp Static. 8000 58 61	62 64 65 66
2200 2075 2025	ESP 0.1 .25 .3	4L1 or 4T1 *VFD Input RPM 712 760 781	460 460 Current 1/2 HP'' Freq. (Hz)	3 3 <b>Sound</b> 63 76 78 78	Modulating Data - Ass 125 74 76 76 78 80	me 1.0 1.0 250 71 74 75 76 77	1.9 2.8* 3125 Inte 500 69 71 72	3.5 ernal Ex 1000 68 70 71	6.3 haust Ca 2000 65 68 69 69 69 69	<b>binet S</b> 4000 61 64 64	V/A Amp Static. 8000 58 61 61	62 64 65
2200 2075 2025 1950	ESP 0.1 .25 .3 .4	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821	460 460 Current 1/2 HP'' Freq. (Hz)	3 3 <b>Sound</b> 63 76 78 78 81	Modulating Data - Ass 125 74 76 76 78	me 1.0 1.0 250 71 74 75 76	1.9 2.8* 3125 Inte 500 69 71 72 73	3.5 ernal Ex 1000 68 70 71 71 71	6.3 haust Ca 2000 65 68 69 69 69	<b>binet S</b> 4000 61 64 64 65	V/A Amp Static. 8000 58 61 61 61 62	62 64 65 66
2200 2075 2025 1950 1850	ESP 0.1 .25 .3 .4 .5	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864	460 460 Current 1/2 HP'' Freq. (Hz)	3 3 <b>Sound</b> 63 76 78 78 81 83	Modulating Data - Ass 125 74 76 76 78 80	me 1.0 1.0 250 71 74 75 76 77	1.9 2.8* 3125 Inte 500 69 71 72 73 74	3.5 ernal Ex 1000 68 70 71 71 71 72	6.3 haust Ca 2000 65 68 69 69 69 69	<b>binet S</b> 4000 61 64 64 65 66	V/A Amp Static. 8000 58 61 61 61 62 63	62 64 65 66 67
2200 2075 2025 1950 1850 1775	ESP 0.1 .25 .3 .4 .5 .6	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974	460 460 Current 1/2 HP'' Freq. (Hz) dBA	3 3 <b>Sound</b> 63 76 78 78 81 83 84 84 86	Modulating Data - Ass 125 74 76 76 78 80 82	me 1.0 1.0 250 71 74 75 76 77 79 82	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78	3.5 ernal Ex 1000 68 70 71 71 71 72 74 76	6.3 haust Ca 2000 65 68 69 69 69 69 69 72 76	binet S 4000 61 64 65 66 68 70	V/A Amp 5tatic. 8000 58 61 61 62 63 65 65 67	62 64 65 66 67 68
2200 2075 2025 1950 1850 1775	ESP 0.1 .25 .3 .4 .5 .6	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974	460 460 Current <b>1/2 HP''</b> (Hz) dBA dBA	3 3 <b>Sound</b> 63 76 78 78 81 83 84 84 86	Modulating Data - Ass 125 74 76 76 76 78 80 82 83	me 1.0 1.0 250 71 74 75 76 77 79 82	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78	3.5 ernal Ex 1000 68 70 71 71 71 72 74 76	6.3 haust Ca 2000 65 68 69 69 69 69 69 72 76	binet S 4000 61 64 65 66 68 70	V/A Amp 5tatic. 8000 58 61 61 62 63 65 65 67	62 64 65 66 67 68 71
2200 2075 2025 1950 1850 1775 1650	ESP 0.1 .25 .3 .4 .5 .6 .75	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974	460 460 Current 1/2 HP'' Freq. (Hz) dBA	3 3 5 63 76 78 78 81 83 84 83 84 86 Sound	Modulating Data - Ass 125 74 76 76 78 80 82 83 Data - Ass	me 1.0 1.0 250 71 74 75 76 77 79 82 umes .3	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 9125 Inte	3.5 ernal Ex 1000 68 70 71 71 72 74 74 76 rnal Exh	6.3 haust Ca 2000 65 68 69 69 69 72 76 76 haust Cab	binet S 4000 61 64 65 66 68 70 binet S	V/A Amp 5tatic. 8000 58 61 61 62 63 65 67 tatic.	62 64 65 66 67 68
2200 2075 2025 1950 1850 1775 1650 CFM	ESP 0.1 .25 .3 .4 .5 .6 .75 ESP	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974 <b>RPM</b>	460 460 Current <b>1/2 HP''</b> (Hz) dBA dBA	3 3 5ound 63 76 78 78 81 83 84 86 Sound 63	Modulating Data - Ass 125 74 76 76 76 78 80 82 83 Data - Ass 125	me 1.0 1.0 250 71 74 75 76 77 79 82 umes .3 250	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 125 Inte 500	3.5 ernal Ex 1000 68 70 71 71 72 74 76 rnal Exh 1000	6.3 haust Ca 2000 65 68 69 69 69 72 76 76 aust Cab 2000	binet S 4000 61 64 65 66 68 70 5 68 70 5 68 70 5 68 70 5 68 70 5 68 70 5 68 70 5 68 70 5 68 70 5 68 70 68 70 68 70 68 70 68 68 70 68 70 68 70 68 70 68 70 70 70 70 70 70 70 70 70 70	V/A Amp Static. 8000 58 61 61 62 63 65 67 tatic. 8000	62 64 65 66 67 68 71 Blower Outlet dBA @ 51
2200 2075 2025 1950 1850 1775 1650 <b>CFM</b> 2900	ESP 0.1 .25 .3 .4 .5 .6 .75 ESP 0.1	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974 <b>RPM</b> 840	460 460 Current <b>1/2 HP''</b> (Hz) dBA dBA	3 3 5 63 76 78 78 81 83 84 86 Sound 63 82	Modulating Data - Ass 125 74 76 76 76 78 80 82 83 Data - Ass 125 79	me 1.0 1.0 250 71 74 75 76 77 79 82 umes .3 250 76	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 125 Inte 500 73	3.5 ernal Ex 1000 68 70 71 71 72 74 76 rnal Exh 1000 71	6.3 haust Ca 2000 65 68 69 69 69 72 76 naust Cab 2000 68	binet S 4000 61 64 65 66 68 70 binet S 4000 65	V/A Amp Static. 8000 58 61 61 62 63 65 67 tatic. 8000 62	62 64 65 66 67 68 71 Blower Outlet dBA @ 5 66
2200 2075 2025 1950 1850 1775 1650 <b>CFM</b> 2900 2825	ESP 0.1 .25 .3 .4 .5 .6 .75 ESP 0.1 .25	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974 <b>RPM</b> 840 875	460 460 Current <b>1/2 HP''</b> (Hz) dBA dBA	3 3 5 63 76 78 78 81 83 84 86 Sound 63 82 83	Modulating Data - Ass 125 74 76 76 76 78 80 82 83 Data - Ass 125 79 80 80 80 80 80 80 80 80 80 80 80 80 80	me 1.0 1.0 250 71 74 75 76 77 79 82 umes .3 250 76 78	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 9125 Inte 500 73 74	3.5 ernal Ex 1000 68 70 71 71 72 74 76 rnal Exh 1000 71 73	6.3         haust Ca         2000         65         68         69         69         72         76         haust Cat         2000         68         70	binet S 4000 61 64 64 65 66 68 70 binet S 4000 65 67	V/A Amp Static. 8000 58 61 61 62 63 65 67 tatic. 8000 62 64	62 64 65 66 67 68 71 Blower Outlet dBA @ 5 66 67
2200 2075 2025 1950 1850 1775 1650 <b>CFM</b> 2900 2825 2800	ESP 0.1 .25 .3 .4 .5 .6 .75 ESP 0.1 .25 .3	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974 <b>RPM</b> 840 875 886	460 460 Current <b>1/2 HP''</b> Freq. (Hz) dBA "1 HP'' \$ Freq. (Hz)	3 3 3 63 63 76 78 78 81 83 84 86 <b>Sound</b> 63 82 83 83	Modulating  Data - Ass  125 74 76 76 76 78 80 82 83 Data - Ass 125 79 80 81	me 1.0 1.0 250 71 74 75 76 77 79 82 umes .3 250 76 78 78	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 500 73 74 500 73 74 75	3.5 ernal Ex 1000 68 70 71 71 72 74 76 rnal Ext 1000 71 73 73	6.3         haust Ca         2000         65         68         69         69         72         76         naust Cat         2000         68         70         71	binet S 4000 61 64 64 65 66 68 70 binet S 4000 65 67 67 67	V/A Amp Static. 8000 58 61 61 62 63 65 67 tatic. 8000 62 64 64 64	62 64 65 66 67 68 71 Blower Outlet dBA @ 5 66 67 68
2200 2075 2025 1950 1850 1775 1650 <b>CFM</b> 2900 2825 2800 2725	ESP 0.1 .25 .3 .4 .5 .6 .75 .6 .75 .75 .01 .25 .3 .4	4L1 or 4T1 *VFD Input <b>RPM</b> 712 760 781 821 864 908 974 <b>RPM</b> 840 875 886 909	460 460 Current <b>1/2 HP''</b> Freq. (Hz) dBA "1 HP'' \$ Freq. (Hz)	3 3 3 63 63 76 78 78 81 83 84 86 <b>Sound</b> 63 82 83 83 83 83	Modulating  Data - Ass  125 74 76 76 76 78 80 82 83 Data - Ass 125 79 80 81 81 81	me 1.0 1.0 250 71 74 75 76 77 79 82 <b>umes .3</b> 250 76 78 78 78 79	1.9 2.8* 3125 Inte 500 69 71 72 73 74 76 78 125 Inte 500 73 74 75 76	3.5 ernal Ex 1000 68 70 71 71 72 74 76 rnal Ext 1000 71 73 73 74	6.3         haust Ca         2000         65         68         69         69         72         76         Daust Cat         2000         68         70         71         73	binet S 4000 61 64 64 65 66 68 70 binet S 4000 65 67 67 68	V/A Amp Static. 8000 58 61 61 62 63 65 67 tatic. 8000 62 64 64 64 64 65	62 64 65 66 67 68 71 Blower Outlet dBA @ 5 66 67 68 68 69

Indianapolis\_3035 N. Shadeland Ave., Indianapolis, IN 46226\_800.MMC.HVAC •• Sparks\_905 Southern Way, Sparks, NV 89431\_800.884.4MMC •• Longview\_201 Kodak Blvd., Longview, TX 75602\_903.248.4800