

ZP16K5E-PFV

HFC, R-410A, 60 Hz, 1 - Phase, 208/230 V [.Also Available with Variable Frequency Drives](#)

Air Conditioning

Production Status: Available for sale to all U.S. customers. Please check with your local Emerson Climate Technologies Representative for international availability.

Summary

Performance		
Evaporator Temp. (°F)	45	50
Condensing Temp. (°F)	130	100
Return Gas Temp. (°F)	65	70
Liquid Temp. (°F)	115	85
Capacity (BTU/hr)	15500	21500
Power (W):	1660	1080
Current (Amps):	7.3	4.8
EER(BTU/Wh):	9.3	20
Mass Flow (lbs/hr):	228	264
Sound Data @ 45 / 130		
Sound Power (dBA):	66 Avg	71 Max
Vibration mils(peak-peak):	2.0 Avg	3.0 Max
Record Date:	2017-03-01	
Mechanical		
Displacement (in^3/Rev):	.92	
Displacement (ft^3/Hr):		
Overall Length (in):	9.56	
Overall Width (in):	9.56	
Overall Height (in):	15.27	
Mounting Length (in):	7.50	
Mounting Width (in):	7.50	

Mounting Height (in):	16.02
Suction Size (in),Type:	3 / 4 Stub
Discharge Size (in),Type:	1 / 2 Stub
Initial Oil Charge (oz):	25
Oil Recharge (oz):	21
Net Weight (lbs):	47.4
Internal Free Volume (in^3):	122.7

Horse Power:

*Overall compressor height on Copeland Brand Product's specified mounting grommets.

LRA High* (Amps):	48.0
LRA Low*(Amps):	
LRA Half Winding (Amps):	
MCC (Amps):	14
Max Operating Current (Amps):	9.1
RLA, MCC/1.4(use for contactor selection)(Amps):	10.0
RLA, MCC/1.56(use for breaker & wire size selection)(Amps):	9.0
RPM:	3500
Box IP :	21
UL File No:	SA-2337
UL File Date:	2003-12-16

*Low and High refer to the low and high nominal voltage ranges for which the motor is approved.

Capacitors

Type	Part No	Low MFD	High MFD	Volts	User Description
Run Capacitor	014-0064-06	30.0	0.0	370	
Start Capacitor	014-0061-27	88.0	106.0	330	OPTIONAL

Alternate Applications

Refrigerant	Voltage	Phase	Frequency	Application
No data available in table				

Service Parts

Service Parts				
Reference	Component	Quantity	Description	Comment
1	918-0052-00	1	CRANKCASE HEATER KIT	240V 40W WRAP AROUND
1	918-0052-01	1	CRANKCASE HEATER KIT	120V 40W WRAP AROUND
2	527-0044-15	1	SPACER - MOUNTING ASSM	
7	998-0510-38	1	VLV KIT 3/4"SWT/1 1/4-12UNC	SUCTION ROTALOCK
7	998-0510-98	1	VLV KIT 1/2"SWT/1-14UNC	DISCHARGE ROTALOCK
13	914-0037-10	1	RUN CAP KIT W/CLAMP	
99	529-0060-24	1	POWER CABLE-MOLDED PLUG	
99	998-0034-01	1	ADAP KIT 3/4"SWT / 1 1/4 RL	SWEAT TO ROTALOCK ADAPTER KIT SUCTION
99	998-0034-07	1	ADAP KIT 1 1/4 RL / 3/4"SWT	ROTALOCK TO SWEAT ADAPTER KIT SUCTION
99	998-0034-15	1	SERV ADAPTOR KIT 1/2 STUB	SWEAT TO ROTALOCK ADAPTER KIT DISCHARGE

Accessories

Accessories		
Category	Part Number	Description
(1) Variable Frequency Drive	EVM-322011- E20ENN	EVM, 3Ø, 200-240v, Output 200-240v@11A, Pro, IP20, Standard, No Options, Frame 1
(1) Variable Frequency Drive	EVH-322011- R54BDB	EVH, 3Ø, 200-240v, Output 200-240v@11A, LCD Keypad, IP54, With 5% DC Link Choke, With Bypass, Frame H3X
(1) Variable Frequency Drive	EVH-322011- R54BDN	EVH, 3Ø, 200-240v, Output 200-240v@11A, LCD Keypad, IP54, With 5% DC Link Choke, No Options, Frame 1
(1) Variable Frequency Drive	EVH-322011- R21BEN	EVH, 3Ø, 200-240v, Output 200-240v@11A, LCD Keypad, IP21, With 5% DC Link Choke + EMI Filter, No Options, Frame 1
(1) Variable Frequency Drive	EVH-322011- R21BDN	EVH, 3Ø, 200-240v, Output 200-240v@11A, LCD Keypad, IP21, With 5% DC Link Choke, No Options, Frame 1
(1) Variable Frequency Drive	EVH-322011- R54BEN	EVH, 3Ø, 200-240v, Output 200-240v@11A, LCD Keypad, IP54, With 5% DC Link Choke + EMI Filter, No Options, Frame 1

Category	Part Number	Description
(1) Variable Frequency Drive	EVM-322011-E20EFN	EVM, 3Ø, 200-240v, Output 200-240v@11A, Pro, IP20, With add on EMI filter, No Options, Frame 1
(1) Variable Frequency Drive	EVM-322011-N20MFN	EVM, 3Ø, 200-240v, Output 200-240v@11A, Basic, IP20, With add on EMI filter, No Options, Frame 1
(1) Variable Frequency Drive	EVM-322011-N20MNN	EVM, 3Ø, 200-240v, Output 200-240v@11A, Basic, IP20, Standard, No Options, Frame 1

Electrical Components

Electrical Components	
Part No: 071-0509-45	
Usage Description: Internal Protector	
<u>Vendor Part Number</u>	
15HM1746	
<u>Vendor Name</u>	
SENSATA	
Part No: 071-0640-02	Stator
Usage Description: Internal Protector	Part No: 546-5016-06
<u>Vendor Part Number</u>	Usage Description: Stator
UP5FY0825-C11	Resistance: +/-7%
<u>Vendor Name</u>	Start Wdg: 2.13
UBUKATA	Run Wdg: 1.39
Stator	Stator
Part No: 546-5251-10	Part No: 846-5016-06
Usage Description: Stator	Usage Description: Stator
Resistance: +/-7%	Resistance: +/-7%
Start Wdg: 2.30	Start Wdg: 2.13
Run Wdg: 1.53	Run Wdg: 1.39
Potential	Start Capacitor
Part No: 040-0166-37	Part No: 014-0061-27
Usage Description: Potential Relay	Low MFD: 88.0
<u>Vendor Part Number</u>	Type:Start Capacitor
RVA2AE6D-946	High MFD: 106.0
<u>Vendor Name</u>	Usage Description: Start Capacitor
ELECTRICA	Volts: 330
Run Capacitor	
Part No: 014-0064-06	

Low MFD: 30.0

Type:Run Capacitor

High MFD: 0.0

Usage Description: Run Capacitor

Volts: 370

Nomenclature

ZP16K5E-PFV

Family Series

Z: Scroll

Application Range

P: A/C - R-410A/B

Capacity

16K: Capacity Multiplier-1000

Oil Type

E: Polyol Ester

Motor Type

P: 1 Phase/Capacitor Run, Permanent Split Capacitor

Motor Protection

F: Internal Inherent Protection

Voltage

V: 60Hz (208/230-1) 50Hz (-)

Miscellaneous

Alternate Application

Refrigerant	Freq	Phase	Voltage	Application
-------------	------	-------	---------	-------------

No data available in table

Nomenclature

[ZP16K5E-PFV](#)

Date	Data Group	Field	Old Data	New Data
27-May-2005	Status	Status	P	A
14-Jun-2005	Sound	Sound Max	69	71
27-May-2005	Sound	Sound Max	71	69

Date	Data Group	Field	Old Data	New Data
27-May-2005	Sound	Sound Stop	60	56
27-May-2005	Sound	Sound Stop Max	69	64
05-May-2005	Sound	Sound Stop	56	60
05-May-2005	Sound	Sound Stop Max	64	69
22-Oct-2008	RatingRefNo	RatingRefNo	08-1125	08-1134
-----	-----	-----	-----	-----